



PUSH BUTTON DOORBELL

BEFORE INSTALLING

Before you begin, read the installation instructions below. Observe all local building and safety codes. For the following installation instructions it is assumed that a standard two-wire electrical system is already in place for the doorbell.

INSTRUCTIONS

Unpack and inspect the product for any shipping damages. If you find damages, do not install. Contact Customer Service at 1.866.855.2284. If you need assistance or have questions while installing your doorbell contact Customer Service.

We recommend consulting a professional if you are unfamiliar with installing hardware or electrical fixtures. Hardwired doorbells should be installed by a licensed electrician. Signature Hardware accepts no liability for any damage to the door frame or wall, or for personal injury during installation.

TOOLS AND MATERIALS:



Screwdriver



Electrical tape



voltage tester



Masking Tape



Long-nose pliers



Wire Stripper

INSTALLATION

- 1. Turn off the source of electricity to the doorbell.** Turn off the circuit that supplies electricity to the doorbell.
- 2. Remove the old doorbell mechanism.** Remove the screws holding the old doorbell to the door frame or wall. If the mounting screws are not visible, you may need to remove the cover plate to reach them.
- 3. Detach the wires from the old doorbell mechanism.** Carefully pull the doorbell mechanism away from the wall. Use a voltage tester to check the wires and ensure that the power is off. Use a screwdriver to disconnect the wires from the old doorbell mechanism. Use a short length of masking tape to temporarily tape the wires to the open hole to prevent the wires from sliding back into the wall. The wires are interchangeable so there's no need to remember which wire goes with which terminal.
- 4. Connect the wires to the new switch.** Remove the masking tape and use a screwdriver to connect each wire to a screw terminal on the new doorbell mechanism. You may find it helpful to use long nose pliers to hold the wire while you do this.
- 5. Affix the new doorbell.** Fasten the new doorbell to the door frame or wall using the screws provided.
- 6. Restore power and test.** Turn on the circuits that supply electricity to the doorbell, then push the doorbell to make sure it works. If it doesn't work, have a licensed electrician check the wiring.